



Comparison Chart for GV-Eye / GV-iView / GV-AView

Model	GV-Eye	GV-iView	GV-AView
Versions	V2.1 (for iOS) V2.1.1 (for Android)	V2.3.2 / HD V1.2.2 (for iOS)	V1.3.1 (for Android)
Software			
Supported OS	iOS 6.1 or later Android 4.0 or later	iOS 4.3.3 or later	Android 2.2 or later
Resolution	Up to 5 MP	VGA / CIF	
Codec	MPEG4, MJPEG and H.264	MJPEG	
Hosts			
GV-DVR/NVR	V8.6.2.0	V8.6.2.0	V8.6.2.0
GV-VMS	V14.10	No	
GV-Mobile Server	V1.4.2.0		
GV-Recording Server	V1.2.5.0		
GV-SNVR	V1.10		
GV-IP Camera	Yes		
GV-Video Server	Yes		
GV-Compact DVR	Yes		
Features			
Snapshot	Yes		
PIP	Yes		
Recording	Yes		
PTZ	Yes		
Fisheye Dewarping	Yes *An in-app purchase	No	
I/O Trigger	Yes		
Speaker	Yes	No	
Stream Switch	Yes	No	
Hardware Decode (Android)	Yes	No	
Remote Playback	Yes		
License			
Max. number of channels	6 channels x 6 pages Up to 36 live views	6 channels x 6 pages Up to 32 live views	

All specifications are subject to change without notice.

Note for GV-Eye V2.1:

- The following functions will be supported in a future version.
 - Playing back remotely from GV-DVR/NVR
 - Enabling recording and triggering I/O devices from GV-VMS V15.10
 - Playing back remotely and enabling PTZ function from GV-SNVR
- Recording can be enabled with the following GV-Video Server only.
 - GV-VS04A (Firmware V1.06 or later)
 - GV-VS11 (Firmware V1.03 or later)
 - GV-VS12 (Firmware V1.07 or later)
 - GV-VS14 (Firmware V1.01 or later)
- Assigning NAS storage path is supported by the following GV-IP Cameras only.
 - GV-Target IP Cameras (Firmware V1.02 or later)
 - GV-IP Cameras (Firmware V3.0 or later)
- The Speaker function only works when GV-Mobile Server and GV-DVR/NVR are installed on the same computer.